

Propagators of isochronous an-harmonic oscillators and Mehler formula for the x-Hermite polynomials

Andrey M. Pupasov-Maksimov*
 Depto. de Matemática, ICE,
 Universidade Federal de Juiz de Fora, MG, Brasil
 (Dated: February 9, 2015)

It is shown that fundamental solutions $K^\sigma(x, y; t) = \langle x | e^{-i H^\sigma t} | y \rangle$ of the non-stationary Schrödinger equation (Green functions, or propagators) for the rational extensions of the Harmonic oscillator $H^\sigma = H_{\text{osc}} + \Delta V^\sigma$ are expressed in terms of elementary functions only. An algorithm to calculate explicitly K_σ for an arbitrary $\sigma \in \mathbb{N}$ is given, compact expressions for $K^{\{1,2\}}$ and $K^{\{2,3\}}$ are presented. A generalization of the Mehler's formula to the case of exceptional Hermite polynomials is given.

Introduction

In this work we present new examples of exactly-solved propagators in one-dimensional quantum mechanics. We consider rationally extended Harmonic oscillators [1]. In this case the evolution of wave packets is periodic, we have so called isochronous anharmonic oscillators [2]. This periodicity is related with the quasi-equidistant structure of the spectrum of the Hamiltonian [3].

The simplest rational extension is given by the potential [4]

$$V^{\{1,2\}}[x] = \frac{x^2}{4} + 2 \left(1 + 2 \frac{(x^2 - 1)}{(x^2 + 1)^2} \right), \quad (1)$$

which leads to the quasi-equidistant spectrum [3], $E_n = n + \frac{1}{2}$, where $n \in \mathbb{N}_0 \setminus \{1, 2\}$, for the stationary Schrödinger equation.

Another example is the two-well perturbation of the oscillator

$$V^{\{2,3\}}[x] = \frac{x^2}{4} + 2 \left(1 + 4x^2 \frac{x^4 - 9}{(x^4 + 3)^2} \right) \quad (2)$$

with the quasi-equidistant spectrum, $E_n = n + \frac{1}{2}$, $n \in \mathbb{N}_0 \setminus \{2, 3\}$.

Note that each rational extension V^σ of the Harmonic oscillator is defined by a sequence of levels $\sigma \in \mathbb{N}$ which are deleted from the spectrum by Darboux-Crum transformations [1]. Darboux transformations represent a powerful tool to manipulate physical properties of one-dimensional quantum systems, [5]. In the case of shape-invariant potentials, relations between propagators were studied in [6, 7]. A more general approach for the calculations of propagators for potentials generated by an arbitrary chain of Darboux transformations were developed in [8–11].

As a particular example, propagators $K^{\{k,k+1\}}$ for the $V^{\{k,k+1\}}$ family were defined through a generating function $S(x, y; t|J)$ which contains the error-function [11]. Here we will further simplify and extend this result. First, we will show that the propagator K^σ for an arbitrary potential V^σ is expressed by elementary functions only. In the case of potentials (1) and (2) we get the following propagators

$$K^{\{1,2\}}(x, y; t) = e^{-2it} K_{\text{osc}}(x, y; t) \left(1 - \frac{4i \sin t [xy - e^{it}]}{(1+x^2)(1+y^2)} \right), \quad (3)$$

$$K^{\{2,3\}}(x, y; t) = e^{-2it} K_{\text{osc}}(x, y; t) \left(1 - \frac{8i \sin t [xy(x^2y^2 - 3) - 3(x^2 + y^2) \cos t - 3i(x^2y^2 + 1) \sin t]}{(3+x^4)(3+y^4)} \right), \quad (4)$$

where the propagator of the Harmonic oscillator [12] is used

$$K_{\text{osc}}(x, y, t) = \frac{1}{\sqrt{4\pi i \sin t}} e^{\frac{i[(x^2+y^2) \cos t - 2xy]}{4 \sin t}}. \quad (5)$$

*Electronic address: pupasov.maksimov@ufjf.edu.br

Second, we will define a rational ansatz to compute propagators K^σ . In the general case, propagators for the rationally extended oscillators have the following structure

$$K^\sigma(x, y; t) = K_{\text{osc}}(x, y; t) \frac{\sum_{k=0}^{\sigma[[[-1]]]+1} Q_k^\sigma(x, y) e^{-i k t}}{\sum_{k=0}^{\sigma[[[-1]]]+1} Q_k^\sigma(x, y)} \quad (6)$$

where $Q_k^\sigma(x, y) = Q_k^\sigma(y, x)$ are some polynomials that can be determined iteratively, which is more efficient than the method based on the generating function [11]. The polynomials $Q_k^\sigma(x, y)$ allow also calculate Green functions $G_\sigma(x, y; E)$ and generalize Melher's formula for the x-Hermite polynomials [13].

I. HARMONIC OSCILLATOR, HERMITE POLYNOMIALS AND POTENTIALS WITH QUASI-EQUIDISTANT SPECTRUM

Consider the hamiltonian of the Harmonic oscillator

$$H_{\text{osc}} = -\partial_{xx}^2 + \frac{x^2}{4}, \quad (7)$$

with eigen-functions defined in terms of probabilistic Hermite polynomials

$$\psi_n(x) = p_n \text{He}_n(x) e^{-\frac{x^2}{4}}, \quad p_n = \left(n! \sqrt{2\pi}\right)^{-\frac{1}{2}}. \quad (8)$$

Rational extensions are defined as the following perturbations of the Harmonic oscillator [13]

$$H^\sigma = -\partial_{xx}^2 + \frac{x^2}{4} - 2\partial_{xx}^2 (\ln \text{Wr}[\psi_\sigma(x), x]), \quad (9)$$

where σ ,

$$\sigma = \{k_1, k_1 + 1, \dots, k_M, k_M + 1\}, \quad |\sigma| = 2M, \quad (10)$$

is a strictly increasing sequence of natural numbers, or a Krein-Adle sequence [20].

Following standard notations of the Mathematica program language we denote by $\sigma[[i]]$ and by $\sigma[[[-1]]]$ i -th element and the last element of this sequence, respectively. A sequence of natural numbers appearing as a subscript, for instance, $\psi_\sigma(x)$, implies a set of elements,

$$\psi_\sigma(x) = \psi_{\{n_1, n_2, \dots, n_{2M}\}}(x) = \{\psi_{n_1}(x), \psi_{n_2}(x), \dots, \psi_{n_{2M}}(x)\},$$

that is, if $(A_n)_{n>0}$ is a sequence of elements, then $A_{\{n_1, \dots, n_m\}}$ is a set of elements. This agreement allows us to write Wronskians in a compact form

$$\text{Wr}[\psi_\sigma(x), x] = \begin{vmatrix} \psi_{\sigma[[1]]}(x) & \psi_{\sigma[[2]]}(x) & \dots & \psi_{\sigma[[[-1]]]}(x) \\ \psi'_{\sigma[[1]]}(x) & \psi'_{\sigma[[2]]}(x) & \dots & \psi'_{\sigma[[[-1]]]}(x) \\ \vdots & \vdots & \ddots & \vdots \\ \psi_{\sigma[[1]]}^{(|\sigma|-1)}(x) & \psi_{\sigma[[2]]}^{(|\sigma|-1)}(x) & \dots & \psi_{\sigma[[[-1]]]}^{(|\sigma|-1)}(x) \end{vmatrix}. \quad (11)$$

Hamiltonians H_{osc} and H^σ can be embedded into a polynomial SUSY algebra [5, 14]

$$LH_{\text{osc}} = H^\sigma L, \quad L^+ L = \prod_{j=1}^{2M} (H_{\text{osc}} - \sigma[[j]]), \quad LL^+ = \prod_{j=1}^{2M} (H^\sigma - \sigma[[j]]), \quad (12)$$

where L is a differential operator of $2M$ -th order [15]

$$Lf(x) = \frac{\text{Wr}[\psi_\sigma(x) \cup \{f(x)\}, x]}{\text{Wr}[\psi_\sigma(x), x]}. \quad (13)$$

Operator L maps the oscillator eigen-functions (8) to the eigen-functions of the rationally extended oscillator

$$\psi_n^\sigma(x) = N_n L \psi_n(x), \quad (14)$$

where a normalization factor is taken into account

$$N_n = \begin{cases} \left(\prod_{j=1}^{2M} (n - \sigma[[j]]) \right)^{-\frac{1}{2}}, & n \notin \sigma, \\ 0, & n \in \sigma. \end{cases} \quad (15)$$

Using explicit form of oscillator eigen-functions (8) and the following identities

$$\begin{aligned} \text{Wr}[\psi_\sigma(x), x] &= e^{-\frac{Mx^2}{2}} \text{Wr}[\text{He}_\sigma(x), x] \prod_{n=1}^{2M} p_{\sigma[[n]]} \\ \ln \text{Wr}[\psi_\sigma(x), x] &= -\frac{Mx^2}{2} + \ln \prod_{n=1}^{2M} p_{\sigma[[n]]} + \ln \text{Wr}[\text{He}_\sigma(x), x] \end{aligned}$$

we can express rationally extended Harmonic oscillators through the Wronskian of probabilistic Hermite polynomials only

$$H_\sigma = -\partial_{xx}^2 + \frac{x^2}{4} - 2\partial_{xx}^2(\ln \text{Wr}[\text{He}_\sigma(x), x]) + 2M. \quad (16)$$

Note (see for instance [1]) that $\text{Wr}[\text{He}_\sigma(x), x]$ (for the chosen class of σ) is the polynomial of x^2 and

$$\deg_x \text{Wr}[\text{He}_\sigma(x), x] = \sum_{n=1}^{2M} (\sigma[[n]] - n + 1).$$

It is convenient to introduce normalized polynomials $h_n(x)$

$$h_n(x) = p_n \text{He}_n(x), \quad (17)$$

and the corresponding normalized exceptional Hermite polynomials

$$h_n^\sigma(x) = N_n \text{Wr}[h_\sigma \cup h_n, x] \quad (18)$$

Finally, we define compact notations

$$W(x) = \text{Wr}[\psi_\sigma(x), x], \quad \hat{W}(x) = \text{Wr}[\text{He}_\sigma(x), x], \quad (19)$$

$$W_n(x) = \text{Wr}[\psi_{\sigma \setminus \{\sigma[[n]]\}}(x), x], \quad \hat{W}_n(x) = \text{Wr}[\text{He}_{\sigma \setminus \{\sigma[[n]]\}}(x), x], \quad (20)$$

$$\hat{L}f = \frac{\text{Wr}[\text{He}_\sigma(x) \cup \{f\}, x]}{\text{Wr}[\text{He}_\sigma(x), x]}. \quad (21)$$

Note that

$$W(x) = e^{-\frac{Mx^2}{2}} \hat{W}(x) \prod_{n=1}^{2M} p_{\sigma[[n]]}, \quad W_n(x) = e^{-\frac{(2M-1)x^2}{4}} \hat{W}_n(x) p_{\sigma[[n]]}^{-1} \prod_{j=1}^{2M} p_{\sigma[[j]]}, \quad (22)$$

$$Le^{-\frac{x^2}{4}} f = e^{-\frac{x^2}{4}} \hat{L}f. \quad (23)$$

II. PROPAGATORS OF RATIONALLY EXTENDED HARMONIC OSCILLATORS

A. Generating function formalism

The Schrödinger equation for the Green function reads

$$(i\partial_t - H)_x K(x, y; t) = 0, \quad K(x, y, 0) = \delta(x - y). \quad (24)$$

If two Hamiltonians H_0 and H_N are related by N -th order Darboux transformation which remove N levels from the spectrum of H_0 , then corresponding propagators K_0 and K_N are related as follows [11],

$$K_N(x, y; t) = L_x \sum_{n=1}^N (-1)^n \frac{W_n(y)}{W(y)} \int_y^b K_0(x, z; t) u_n(z) dz. \quad (25)$$

In the case of rationally extended Harmonic oscillators $b = \infty$, $N = |\sigma|$, and the transformation solutions coincide with Harmonic oscillator eigenfunctions $u_n = \psi_{\sigma[[n]]}(z)$.

Using (22) we can replace Wronskians of wave functions by Wronskians of Hermite polynomials

$$K^\sigma(x, y; t) = \sum_{n=1}^{2M} (-1)^n e^{\frac{y^2}{4}} \frac{\hat{W}_n(y)}{\hat{W}(y)} L_x \int_y^\infty K_{\text{osc}}(x, z; t) e^{-\frac{z^2}{4}} \text{He}_{\sigma[[n]]}(z) dz \quad (26)$$

The occurring integrals $\int_y^\infty K_{\text{osc}}(x, z; t) e^{-\frac{z^2}{4}} \text{He}_n(z) dz$ can be represented as derivatives of the generating function with respect to the auxiliary current J

$$\int_y^\infty K_{\text{osc}}(x, z; t) e^{-\frac{z^2}{4}} \text{He}_{\sigma[[n]]}(z) dz = [\text{He}_{\sigma[[n]]}(\partial_J) S(J)]_{J=0} = \left[\sum_{k=0}^{\sigma[[n]]} h_{\sigma[[n]],k} \frac{\partial^k S(J)}{\partial J^k} \right]_{J=0},$$

where $h_{m,k}$ are coefficients of the He_m . The generating function reads

$$S(J|x, y, t) = \frac{1}{2} e^{\left(\frac{-it}{2} - \frac{x^2}{4}\right)} R \left[i J \sqrt{2i \sin t} e^{-\frac{it}{2}}, \frac{x e^{-\frac{it}{2}}}{i \sqrt{2i \sin t}} \right] E[J, x, y, t] \quad (27)$$

where

$$\begin{aligned} R \left[i J \sqrt{2i \sin t} e^{-\frac{it}{2}}, \frac{x e^{-\frac{it}{2}}}{i \sqrt{2i \sin t}} \right] &= \exp(J(i J \sin t + x) \exp(-it)), \\ E[J, x, y, t] &= \left(1 + \text{erf} \left[-J \sqrt{i \sin t} e^{-\frac{it}{2}} - \frac{i \sqrt{i}}{2 \sqrt{\sin t}} \left(y e^{\frac{it}{2}} - x e^{-\frac{it}{2}} \right) \right] \right), \\ \text{erf}(z) &= \frac{2}{\sqrt{\pi}} \int_0^z \exp(-t^2) dt. \end{aligned}$$

Function R is the generating function of rescaled Hermite polynomials (see also Appendix A)

$$R[z\sqrt{\alpha}, \frac{x}{\sqrt{\alpha}}] = \exp\left(xz - \frac{\alpha z^2}{2}\right) = \sum_{n=0}^{\infty} \text{He}_n^{[\alpha]}(x) \frac{z^n}{n!}.$$

For the compact writing we define

$$\alpha = -2i \sin t e^{it} = 1 - e^{2it}, \quad e^{-\frac{it}{2}} \sqrt{i \sin t} = \frac{1}{\sqrt{2}} (1 - e^{-2it})^{\frac{1}{2}}. \quad (28)$$

In what follows we need derivatives of generating functions R , E and

$$E_0[x, y; t] = E[0, x, y, t] = \left(1 + \text{erf} \left[\frac{i \sqrt{i}}{2 \sqrt{\sin t}} \left(x e^{-\frac{it}{2}} - y e^{\frac{it}{2}} \right) \right] \right).$$

1. J -derivatives of R -function

$$\frac{k!}{(k-m)!} \left(\partial_J^{k-m} R[J\sqrt{\alpha} e^{-it}, \frac{x}{\sqrt{\alpha}}] \right)_{J=0} = \frac{k!}{(k-m)!} \text{He}_{k-m}^{[\alpha]}(x) e^{-i(k-m)t} = e^{-i(k-m)t} \frac{d^m}{dx^m} \text{He}_k^{[\alpha]}(x) \quad (29)$$

2. J -derivatives of E -function

$$\left(\frac{\partial^{m+1} E[J]}{\partial J^{m+1}} \right)_{J=0} = K_{\text{osc}}(x, y; t) e^{\frac{x^2-y^2}{4}} e^{\frac{-i t}{2}} 2i \sin t \sum_{j=0}^m q_{j,m+1}(x, y) e^{-i t j} \quad (30)$$

3. x -derivatives of E_0 -function

$$\frac{\partial^{k+1} E_0[x, y, t]}{\partial x^{k+1}} = K_{\text{osc}}(x, y; t) e^{\frac{x^2-y^2}{4}} e^{\frac{-i t}{2}} \left(\frac{1}{2i \sin t} \right)^k \sum_{j=0}^k w_{j,m+1}(x, y) e^{-i t j} \quad (31)$$

4. Mixed derivatives of E -function

$$\frac{\partial^k}{\partial x^k} \left(\frac{\partial^{m+1} E[J]}{\partial J^{m+1}} \right)_{J=0} = \left(\frac{1}{2i \sin t} \right)^{k-1} e^{\frac{-i t}{2}} K_{\text{osc}}(x, y; t) e^{\frac{x^2-y^2}{4}} \sum_{j=0}^{m+k} q_{j,m+k+1}(x, y) e^{-i t j}. \quad (32)$$

In the above expressions $q_{i,j}$ and $w_{k,m}$ are some polynomials.

Now we will substitute these derivatives to calculate

$$[\text{He}_{\sigma[[j]]} (\partial_J) S(J)]_{J=0} = \frac{e^{\frac{-i t}{2} - \frac{x^2}{4}}}{2} \left[\sum_{k=0}^{\sigma[[j]]} h_{\sigma[[j]],k} \sum_{m=0}^k C_m^k \left(\partial_J^{k-m} R[J\sqrt{\alpha} e^{-i t}, \frac{x}{\sqrt{\alpha}}] \right) (\partial_J^m E[J, x, y, t]) \right]_{J=0}. \quad (33)$$

Consider first the following double sum

$$\left[\sum_{k=0}^{\sigma[[j]]} h_{\sigma[[j]],k} \sum_{m=0}^k \frac{k!}{m!(k-m)!} \left(\partial_J^{k-m} R[J\sqrt{\alpha} e^{-i t}, \frac{x}{\sqrt{\alpha}}] \right) (\partial_J^m E[J, x, y, t]) \right]_{J=0}$$

We will change the order of summation ($k, m \rightarrow m, k$), that is we will fix m and calculate first sum by $k \in (\sigma[[j]] - m, \sigma[[j]])$.

$$\begin{aligned} & \left[\sum_{k=0}^{\sigma[[j]]} \sum_{m=0}^k h_{\sigma[[j]],k} \frac{1}{m!} e^{-i(k-m)t} \frac{d^m}{dx^m} \text{He}_k^{[\alpha]}(x) (\partial_J^m E[J, x, y, t]) \right]_{J=0} = \\ & \left[\sum_{m=0}^{\sigma[[j]]} \frac{1}{m!} (\partial_J^m E[J, x, y, t]) \sum_{k=m}^{\sigma[[j]]} h_{\sigma[[j]],k} e^{-i(k-m)t} \frac{d^m}{dx^m} \text{He}_k^{[\alpha]}(x) \right]_{J=0}. \end{aligned}$$

In the last expression we can change the inferior limit $k = m$ to $k = 0$ since $\frac{d^m}{dx^m} \text{He}_k^{[\alpha]}(x) = 0$ when $k < m$,

$$e^{-i\sigma[[j]]t} \left[\sum_{m=0}^{\sigma[[j]]} \frac{1}{m!} (\partial_J^m E[J, x, y, t]) e^{i m t} \frac{d^m}{dx^m} \sum_{k=0}^{\sigma[[j]]} h_{\sigma[[j]],k} (e^{2i t})^{\frac{\sigma[[j]]-k}{2}} \text{He}_k^{[\alpha]}(x) \right]_{J=0}.$$

Afterwards we note that $h_{\sigma[[j]],k} (e^{2i t})^{\frac{\sigma[[j]]-k}{2}} = h_{\sigma[[j]],k}^{[1-\alpha]}$ (see Appendix A, (55)),

$$e^{-i\sigma[[j]]t} \left[\sum_{m=0}^{\sigma[[j]]} \frac{1}{m!} (\partial_J^m E[J, x, y, t]) e^{i m t} \frac{d^m}{dx^m} \sum_{k=0}^{\sigma[[j]]} h_{\sigma[[j]],k}^{[1-\alpha]} \text{He}_k^{[\alpha]}(x) \right]_{J=0}.$$

The sum by k represent the umbral composition (57) for the generalized Hermite polynomials $\text{He}_k^{[\alpha]}(x)$ [16], which yields

$$e^{-i\sigma[[j]]t} \left[\sum_{m=0}^{\sigma[[j]]} \frac{1}{m!} (\partial_J^m E[J, x, y, t]) e^{i m t} \frac{d^m}{dx^m} \text{He}_{\sigma[[j]]}(x) \right]_{J=0}.$$

As a result we obtain the following intermediate expression for the propagator

$$K^\sigma = \frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2}{4}} \frac{\hat{W}_j(y)}{\hat{W}(y)} L_x e^{-\frac{x^2}{4}} \sum_{m=0}^{\sigma[[j]]} \frac{1}{m!} (\partial_J^m E[J, x, y, t])_{J=0} e^{-i(\sigma[[j]]-m)t} \frac{d^m}{dx^m} \text{He}_{\sigma[[j]]}(x) .$$

We split the last expression in two terms $K^\sigma = K_E + K_R$, where the first term contains error function in $E_0(x, y; t)$ whereas the second term contains elementary functions only

$$K_E = \frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2}{4}} \frac{\hat{W}_j(y)}{\hat{W}(y)} L_x e^{-\frac{x^2}{4}} e^{-i\sigma[[j]]t} E_0[x, y, t] \text{He}_{\sigma[[j]]}(x) ,$$

$$K_R = \frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2}{4}} \frac{\hat{W}_j(y)}{\hat{W}(y)} L_x e^{-\frac{x^2}{4}} e^{-i\sigma[[j]]t} \sum_{m=1}^{\sigma[[j]]} \frac{1}{m!} (\partial_J^m E[J, x, y, t])_{J=0} e^{imt} \frac{d^m}{dx^m} \text{He}_{\sigma[[j]]}(x) .$$

Changing operator L by $\hat{L}$ with the aids of (22) we get

$$K_E = \frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2-x^2}{4}} e^{-i\sigma[[j]]t} \frac{\hat{W}_j(y)}{\hat{W}(y)} \hat{L}_x E_0[x, y, t] \text{He}_{\sigma[[j]]}(x) ,$$

$$K_R = \frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2-x^2}{4}} \frac{\hat{W}_j(y)}{\hat{W}(y)} \hat{L}_x \sum_{m=1}^{\sigma[[j]]} \frac{e^{-i(\sigma[[j]]-m)t}}{m!} (\partial_J^m E[J, x, y, t])_{J=0} \frac{d^m}{dx^m} \text{He}_{\sigma[[j]]}(x) .$$

Let us consider the first term K_E . Though the function E_0 contains non-elementary error function erf it can be seen that $K_E(x, y; t)$ is expressed in terms of elementary functions only. The error function will be cancelled due to the operator $\hat{L}$ as follows

$$K_E = \frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2-x^2}{4}} e^{-i\sigma[[j]]t} \frac{\hat{W}_j(y)}{\hat{W}(y)} \hat{L}_x E_0[x, y, t] \text{He}_{\sigma[[j]]}(x) =$$

$$\frac{e^{-\frac{i}{2}t}}{2} \sum_{j=1}^{2M} (-1)^j e^{\frac{y^2-x^2}{4}} e^{-i\sigma[[j]]t} \frac{\hat{W}_j(y)}{\hat{W}(y)} \left(E_0[x, y, t] \hat{L}_x \text{He}_{\sigma[[j]]}(x) + \frac{\sum_{n=1}^{2M} A_{n,j}(x) \partial_x^n E_0(x, y; t)}{\hat{W}(x)} \right) ,$$

where $A_{n,j}(x)$ are some polynomials in x . By the definition (21) of the operator $\hat{L}$ we have $\hat{L}_x \text{He}_{\sigma[[j]]}(x) = 0$, therefore

$$K_E = \frac{e^{-\frac{i}{2}t} e^{\frac{y^2-x^2}{4}}}{2\hat{W}(y)\hat{W}(x)} \sum_{j=1}^{2M} (-1)^j e^{-i\sigma[[j]]t} \hat{W}_j(y) \sum_{n=0}^{2M-1} A_{n,j}(x) \partial_x^{n+1} E_0(x, y; t) =$$

$$\frac{e^{-\frac{i}{2}t} e^{\frac{y^2-x^2}{4}}}{2\hat{W}(y)\hat{W}(x)} K_{\text{osc}}(x, y; t) e^{\frac{x^2-y^2}{4}} e^{-\frac{i}{2}t} \sum_{j=1}^{2M} (-1)^j e^{-i\sigma[[j]]t} \hat{W}_j(y) \sum_{n=0}^{2M-1} A_{n,j}(x) \left(\frac{1}{2i \sin t} \right)^n \sum_{l=0}^n w_{l,n+1}(x, y) e^{-itl} =$$

$$\frac{K_{\text{osc}}(x, y; t) e^{-it}}{2\hat{W}(y)\hat{W}(x)} \sum_{j=1}^{2M} (-1)^j e^{-i\sigma[[j]]t} \hat{W}_j(y) \sum_{n=0}^{2M-1} A_{n,j}(x) \left(\frac{1}{2i \sin t} \right)^n \sum_{l=0}^n w_{l,n+1}(x, y) e^{-itl} .$$

Thus we proved that K_E contains elementary functions only. Denote e^{-it} by λ . We can further simplify K_E writing it as a product of K_{osc} and a rational function of x, y and λ ,

$$K_E = \frac{K_{\text{osc}}(x, y; t)}{\hat{W}(y)\hat{W}(x)} \lambda \sum_{j=1}^{2M} (-1)^j \lambda^{\sigma[[j]]} \hat{W}_j(y) \sum_{n=0}^{2M-1} A_{n,j}(x) \left(\frac{\lambda}{1-\lambda^2} \right)^n \sum_{l=0}^n w_{l,n+1}(x, y) \lambda^l =$$

$$\frac{K_{\text{osc}}(x, y; t)}{\hat{W}(y)\hat{W}(x)} \frac{\sum_{n=1}^{4M+\sigma[[-1]]-1} \bar{Q}_n(x, y) \lambda^n}{(1-\lambda^2)^{2M-1}},$$

where $\bar{Q}_n(x, y)$ are some polynomials.

Following the same line we will consider the second term. It can be seen that structures of K_E and K_R coincide, and K_R reads

$$K_R = \frac{K_{\text{osc}}(x, y; t)}{\hat{W}(y)\hat{W}(x)} \frac{\sum_{n=0}^{4M+\sigma[[-1]]-1} \tilde{Q}_n(x, y) \lambda^n}{(1-\lambda^2)^{2M-1}}$$

Combining now K_E and K_R we obtain the following expression

$$K^\sigma = \frac{K_{\text{osc}}(x, y; t)}{\hat{W}(y)\hat{W}(x)} \frac{\sum_{n=0}^{\sigma[[-1]]+1+4M-2} \bar{Q}_n^\sigma(x, y) \lambda^n}{(1-\lambda^2)^{2M-1}} = \frac{K_{\text{osc}}(x, y; t)}{\text{Wr}[h_\sigma(x), x] \text{Wr}[h_\sigma(y), y]} \frac{\sum_{n=0}^{\sigma[[-1]]+1+4M-2} \bar{Q}_n^\sigma(x, y) \lambda^n}{(1-\lambda^2)^{2M-1}}$$

where some constant multiplier $\text{Wr}[h_\sigma(x), x] = C\hat{W}(x)$ is absorbed by redefinition of polynomials $\bar{Q}$.

Consider the limit $t \rightarrow 0$, where $K^\sigma \rightarrow \delta(x-y)$ and $K_{\text{osc}} \rightarrow \delta(x-y)$. From here it follows that the rational λ -depending factor has no pole, therefore

$$\frac{\sum_n^{\sigma[[-1]]+1+4M-2} \bar{Q}_n^\sigma(x, y) \lambda^n}{(1-\lambda^2)^{2M-1}} = \frac{(1-\lambda^2)^{2M-1} \sum_{n=0}^{\sigma[[-1]]+1} Q_n^\sigma(x, y) \lambda^n}{(1-\lambda^2)^{2M-1}} = \sum_{n=0}^{\sigma[[-1]]+1} Q_n^\sigma(x, y) \lambda^n$$

and

$$\sum_{k=0}^{\sigma[[-1]]+1} Q_k^\sigma(x, y) = \text{Wr}[h_\sigma(x), x] \text{Wr}[h_\sigma(y), y]. \quad (34)$$

We finally get a rational ansatz for the propagators

$$K^\sigma(x, y; t) = \frac{K_{\text{osc}}(x, y; t)}{\text{Wr}[h_\sigma(x), x] \text{Wr}[h_\sigma(y), y]} \sum_{k=0}^{\sigma[[-1]]+1} Q_k^\sigma(x, y) e^{-i k t} \quad (35)$$

where $Q_k^\sigma(x, y) = Q_k^\sigma(y, x)$ are some polynomials to be determined.

B. Rational ansatz for the propagators

Substituting into the rational ansatz (35) expansions of propagators in terms of eigen-functions

$$K_{\text{osc}}(x, y; t) = e^{-\frac{x^2+y^2}{4}} \sum_{n=0}^{\infty} h_n(x) h_n(y) \lambda^n, \quad \lambda = e^{-i t}, \quad (36)$$

$$K_\sigma(x, y; t) = \frac{e^{-\frac{x^2+y^2}{4}}}{\text{Wr}[h_\sigma(x), x] \text{Wr}[h_\sigma(y), y]} \sum_{n \in \mathbb{N} \setminus \sigma} h_n^\sigma(x) h_n^\sigma(y) \lambda^n \quad (37)$$

we obtain a system of equations for the polynomial coefficients $Q_k^\sigma(x, y)$. The solution of this system is given by a recursive procedure

$$Q_k^\sigma(x, y) = \frac{1}{h_0(x) h_0(y)} \left(h_k^\sigma(x) h_k^\sigma(y) - \sum_{j=1}^k Q_{k-j}^\sigma(x, y) h_j(x) h_j(y) \right), \quad 0 \leq k \leq \sigma[[-1]]+1. \quad (38)$$

1. Nonlinear connection Lemma for the exceptional Hermite polynomials

Lemma. Given a Krein-Adler sequence $\sigma = \{k_1, k_1 + 1, \dots, k_M, k_M + 1\}$, the corresponding family of (formally normalized) polynomials $h_n^\sigma(x)$ obeys the following relation

$$\sum_{k=0}^{\sigma[[-1]]+1} h_{m-k}(x) h_{m-k}(y) Q_k^\sigma(x, y) = h_m^\sigma(x) h_m^\sigma(y), \quad (39)$$

where polynomials Q_k^σ are given by (38).

Proof. The proof follows from (35), (36), (37) and (38) $\square$

Relation (39) can also be written in terms of wave functions

$$\frac{\sum_{k=0}^{\sigma[[-1]]+1} \psi_{m-k}(x) \psi_{m-k}(y) Q_k^\sigma(x, y)}{\sum_{k=0}^{\sigma[[-1]]+1} Q_k^\sigma(x, y)} = \psi_m^\sigma(x) \psi_m^\sigma(y). \quad (40)$$

There are following properties of the Q^σ -polynomials:

1) Symmetry

$$Q_k^\sigma(x, y) = Q_k^\sigma(y, x)$$

2) Parity

$$Q_k^\sigma(-x, -y) = Q_k^\sigma(x, y)$$

$$Q_{2k}^{\{\sigma\}}(-x, y) = (-1)^{(\deg h_0^\sigma)} Q_{2k}^\sigma(x, y), \quad Q_{2k+1}(-x, y) = -(-1)^{(\deg h_0^\sigma)} Q_{2k+1}^\sigma(x, y)$$

where $\deg h_0^\sigma = \sum_{j=1}^{|\sigma|} (\sigma[[j]] - j + 1) - |\sigma|$.

In the Appendix B we present an example of a non-Krein-Adler sequence $\sigma = \{1\}$ when the nonlinear connection lemma is also holds. We suppose that (39) holds for an arbitrary σ .

2. x -Mehler formula

We first recall the Mehler formula

$$\sum_{n=0}^{\infty} \text{He}_n(x) \text{He}_n(y) \frac{\lambda^n}{n!} = \frac{1}{\sqrt{1-\lambda^2}} e^{\frac{-\lambda^2(x^2+y^2)+2\lambda xy}{2(1-\lambda^2)}}. \quad (41)$$

Using the nonlinear connection lemma (39) we obtain the following generalization of the Mehler formula to the case of exceptional Hermite polynomials

$$\sum_{n=0}^{\infty} h_n^\sigma(x) h_n^\sigma(y) \lambda^n = \frac{1}{\sqrt{2\pi(1-\lambda^2)}} e^{\frac{-\lambda^2(x^2+y^2)+2\lambda xy}{2(1-\lambda^2)}} \sum_{j=0}^{\sigma[[-1]]+1} Q_j^\sigma(x, y) \lambda^j. \quad (42)$$

3. Alternative form of the rationally extended Harmonic oscillators

Consider integral kernels of Hamiltonian operators

$$H_{osc}(x, y) = [-\partial_{xx}^2 + V_{osc}(x)] \delta(x - y) = \sum_{n=0}^{\infty} n \psi_n(x) \psi_n(y), \quad (43)$$

$$H^\sigma(x, y) = [-\partial_{xx}^2 + V^\sigma(x)] \delta(x - y) = \sum_{n=0}^{\infty} n \psi_n^\sigma(x) \psi_n^\sigma(y), \quad (44)$$

using (40) we can represent the second kernel as follows

$$H^\sigma(x, y) = \left[-\partial_{xx}^2 + V_{\text{osc}}(x) - \frac{\sum_{k=0}^{\sigma[[-1]]+1} k Q_k^\sigma(x, y)}{\sum_{j=0}^{\sigma[[-1]]+1} Q_j^\sigma(x, y)} \right] \delta(x - y). \quad (45)$$

From here it follows that

$$\Delta V^\sigma(x) = -2\partial_{xx} \log [\text{Wr}[\psi_\sigma(x), x]] = -\frac{\sum_{k=0}^{\sigma[[-1]]+1} k Q_k^\sigma(x, x)}{\sum_{j=0}^{\sigma[[-1]]+1} Q_j^\sigma(x, x)}$$

4. Green functions

Consider the Green function (resolvent kernel of the Hamiltonian operator)

$$G(x, y; E) = i \int_0^\infty K(x, y; t) e^{iEt} dt$$

The transformation formula for the propagators implies also the following relation for the Green functions

$$G_\sigma(x, y; E) = \frac{1}{W[h_\sigma(x), x]W[h_\sigma(y), y]} \sum_{k=0}^{\sigma[[-1]]+1} Q_k(x, y) G_{\text{osc}}(x, y; E - k) \quad (46)$$

C. Examples

Using first and second excited states of Harmonic oscillator

$$\psi_1(x) = p_1 x e^{-x^2/4} \quad \psi_2(x) = p_2 (x^2 - 1) e^{-x^2/4}$$

we obtain a perturbed Harmonic oscillator potential [17]

$$V_{\{1,2\}}[x] = \frac{x^2}{4} + 2 \left(1 + 2 \frac{(x^2 - 1)}{(x^2 + 1)^2} \right) \quad (47)$$

Connection polynomials read

$$Q_{\{0,1,2,3\}}^{\{1,2\}} = \left\{ \frac{1}{2\pi}, -\frac{xy}{2\pi}, \frac{x^2 y^2 + x^2 + y^2 - 1}{4\pi}, \frac{xy}{2\pi} \right\}.$$

The propagator for the Schrödinger equation with Hamiltonian $K^{(1,2)} = -\partial_x^2 + V^{\{1,2\}}(x)$ has the following compact expression

$$K^{\{1,2\}}(x, y; t) = e^{-2i t} K_{\text{osc}}(x, y; t) \left(1 - \frac{4i \sin t [xy - e^{it}]}{(1+x^2)(1+y^2)} \right), \quad (48)$$

Next simple expression for the propagator we can obtain using second and third excited states of Harmonic oscillator

$$\psi_2(x) = p_2 (x^2 - 1) e^{-x^2/4} \quad \psi_3(x) = p_3 x (x^2 - 3) e^{-x^2/4}.$$

In this case we obtain two-well perturbed Harmonic oscillator potential (potentials $V_{\{k,k+1\}}$ have k shallow minima at their bottom)

$$V_{\{2,3\}}[x] = \frac{x^2}{4} + 2 \left(1 + 4x^2 \frac{x^4 - 9}{(x^4 + 3)^2} \right) \quad (49)$$

Connection polynomials read

$$Q_{\{0,1,2,3,4\}}^{\{2,3\}} = \left\{ \frac{(x^2+1)(y^2+1)}{4\pi}, \frac{xy(3-x^2y^2)}{6\pi}, \frac{x^4y^4+3x^4+3y^4-12x^2y^2-3}{24\pi}, \frac{xy(x^2y^2-3)}{6\pi}, \frac{(x^2-1)(y^2-1)}{4\pi} \right\}.$$

The propagator for the Schrödinger equation with Hamiltonian $H^{\{2,3\}} = -\partial_x^2 + V^{\{2,3\}}(x)$ reads

$$K^{\{2,3\}}(x, y; t) = e^{-2it} K_{\text{osc}}(x, y; t) \left(1 - \frac{8i \sin t [xy(x^2y^2-3) - 3(x^2+y^2) \cos t - 3i(x^2y^2+1) \sin t]}{(3+x^4)(3+y^4)} \right), \quad (50)$$

III. CONCLUSIONS

Propagators

$$K^\sigma(x, y; t) = K_{\text{osc}}(x, y; t) \frac{\sum_{k=0}^{\sigma[[-1]]+1} Q_k^\sigma(x, y) e^{-ikt}}{\sum_{k=0}^{\sigma[[-1]]+1} Q_k^\sigma(x, y)} \quad (51)$$

present a new example of Feynman path integrals that can be calculated analytically [18]. The key formula (38)

$$Q_k^\sigma(x, y) = \frac{1}{h_0(x)h_0(y)} \left(h_k^\sigma(x)h_k^\sigma(y) - \sum_{j=1}^k Q_{k-j}^\sigma(x, y)h_j(x)h_j(y) \right), \quad 0 \leq k \leq \sigma[[-1]] + 1, \quad (52)$$

which define nonlinear connection between x-Hermite and Hermite polynomials can be easily realized in any computer algebra system. One can use these propagators to test various approximations for the corresponding path integrals. Using these propagators wave-packet dynamics in multi-well potentials can be studied analytically.

Appendix A. Rescaled Hermite polynomials, Appell sequences and umbral composition [16]

The generating function of the probabilistic Hermite polynomials reads

$$R[z, x] = \exp\left(xz - \frac{z^2}{2}\right) = \sum_{n=0}^{\infty} \text{He}_n(x) \frac{z^n}{n!}. \quad (53)$$

$$\text{He}_n(x) = \sum_{k=0}^n h_{n,k} x^k,$$

Rescaled Hermite polynomials

$$\text{He}_n^{[\alpha]}(x) = \alpha^{\frac{n}{2}} \text{He}_n\left(\frac{x}{\sqrt{\alpha}}\right), \quad (54)$$

$$h_{n,k}^{[\alpha]} = \alpha^{\frac{(n-k)}{2}} h_{n,k}, \quad (55)$$

with the following generating function

$$R[z\sqrt{\alpha}, \frac{x}{\sqrt{\alpha}}] = \exp\left(xz - \frac{\alpha z^2}{2}\right) = \sum_{n=0}^{\infty} \text{He}_n^{[\alpha]}(x) \frac{z^n}{n!}.$$

form an Appell sequence of polynomials.

Let $A_n(x)$ and $B_n(x)$ be two Appel sequences of polynomials [19] generated by functions $S[x, g]$, $R[x, g]$,

$$S[x, g] = s(g) e^{xg} = \sum_{n=0}^{\infty} A_n(x) \frac{g^n}{n!},$$

$$R[x, g] = r(g)e^{xg} = \sum_{n=0}^{\infty} B_n(x) \frac{g^n}{n!},$$

where $A_n(x) = \sum_{k=0}^n a_{n,k} x^k$, $B_n(x) = \sum_{k=0}^n b_{n,k} x^k$.

Define the umbral composition by the following formula

$$(A_n \circ B)(x) = \sum_{k=0}^n a_{n,k} B_k(x) = \sum_{k=0}^n \sum_{j=0}^k a_{n,k} b_{k,j} x^j. \quad (56)$$

Then the sequence $C_n(x) = (A_n \circ B)(x)$ also is an Appell sequence. Its generating function, denoted by $U[x, g] = S[x, g] \circ R[x, g]$, has the following form

$$U[x, g] = s(g)r(g)e^{xg} = \sum_{n=0}^{\infty} C_n(x) \frac{g^n}{n!}.$$

We can apply these facts to the sequences of generalized Hermite polynomials $He_n^{[\alpha]}(x)$

$$\exp\left(xz - \frac{\alpha z^2}{2}\right) \circ \exp\left(xz - \frac{\beta z^2}{2}\right) = \exp\left(xz - \frac{(\alpha + \beta)z^2}{2}\right).$$

As a result we get the umbral composition of rescaled Hermite polynomials

$$\left(He_n^{[\alpha]} \circ He_k^{[\beta]}\right)(x) = \sum_{k=0}^n h_{n,k}^{[\alpha]} He_k^{[\beta]}(x) = He_n^{[\alpha+\beta]}(x). \quad (57)$$

Appendix B. Q -polynomials for non-Krein-Adler sequence σ

Here we consider an example of the polynomial connection when $\sigma = \{1\}$, which is a non-Krein-Adler sequence [1], and hence, when polynomials h_n^1 do not represent a sequence of orthogonal polynomials. Nevertheless, by direct calculations we can verify that the Non-linear connection lemma is valid in this case. Consider formally normalized product of two wronskians

$$\begin{aligned} h_m^{\{1\}}(x) h_m^{\{1\}}(y) &= \frac{1}{\sqrt{2\pi}(1-m)} \begin{vmatrix} x & h_m(x) \\ 1 & h'_m(x) \end{vmatrix} \begin{vmatrix} y & h_m(y) \\ 1 & h'_m(y) \end{vmatrix} \\ &= \frac{1}{\sqrt{2\pi}(1-m)} (x\sqrt{m}h_{m-1}(x) - h_m(x)) (y\sqrt{m}h_{m-1}(y) - h_m(y)). \end{aligned} \quad (58)$$

Using the recurrence relation for the normalized probabilistic Hermite polynomials

$$x\sqrt{m}h_{m-1}(x) = mh_m(x) + \sqrt{m(m-1)}h_{m-2}(x)$$

we get

$$\begin{aligned} h_m^{\{1\}}(x) h_m^{\{1\}}(y) &= \frac{1}{\sqrt{2\pi}(1-m)} \left([m-1]h_m(x) + \sqrt{m(m-1)}h_{m-2}(x) \right) \left([m-1]h_m(y) + \sqrt{m(m-1)}h_{m-2}(y) \right) \\ &= -\frac{1}{\sqrt{2\pi}} \left(h_m(x) + \frac{\sqrt{m}}{\sqrt{(m-1)}}h_{m-2}(x) \right) \left([m-1]h_m(y) + \sqrt{m(m-1)}h_{m-2}(y) \right) \\ &= \frac{-1}{\sqrt{2\pi}} \left(-h_m(x)h_m(y) + mh_m(x)h_m(y) + \sqrt{m(m-1)}(h_m(x)h_{m-2}(y) + h_m(y)h_{m-2}(x)) + mh_{m-2}(x)h_{m-2}(y) \right) \\ &= \frac{1}{\sqrt{2\pi}} h_m(x)h_m(y) - \frac{1}{\sqrt{2\pi}} (xh_{m-1}(x) - \sqrt{(m-1)}h_{m-2}(x))(yh_{m-1}(y) - \sqrt{(m-1)}h_{m-2}(y)) \\ &\quad - \frac{1}{\sqrt{2\pi}} \sqrt{(m-1)} \left((xh_{m-1}(x) - \sqrt{(m-1)}h_{m-2}(x))h_{m-2}(y) + (yh_{m-1}(y) - \sqrt{(m-1)}h_{m-2}(y))h_{m-2}(x) \right) \end{aligned}$$

$$\begin{aligned}
& -\frac{1}{\sqrt{2\pi}}mh_{m-2}(x)h_{m-2}(y) \\
& = \frac{1}{\sqrt{2\pi}}h_m(x)h_m(y) - \frac{1}{\sqrt{2\pi}}(xh_{m-1}(x)yh_{m-1}(y) + (m-1)h_{m-2}(x)h_{m-2}(y)) \\
& + \frac{1}{\sqrt{2\pi}}2(m-1)h_{m-2}(x)h_{m-2}(y) \\
& - \frac{1}{\sqrt{2\pi}}mh_{m-2}(x)h_{m-2}(y) \\
& = \frac{1}{\sqrt{2\pi}}(h_m(x)h_m(y) - xyh_{m-1}(x)h_{m-1}(y) - h_{m-2}(x)h_{m-2}(y))
\end{aligned}$$

That is, polynomials $h_m^{\{1\}}(x)h_m^{\{1\}}(y)$ satisfy to the following 3-term representation

$$h_m^{\{1\}}(x)h_m^{\{1\}}(y) = \sum_{k=0}^2 h_{m-k}(x)h_{m-k}(y)Q_k^{\{1\}}(x, y),$$

where

$$\begin{aligned}
Q_0^{\{1\}}(x, y) &= \frac{1}{\sqrt{2\pi}}, \\
Q_1^{\{1\}}(x, y) &= -\frac{xy}{\sqrt{2\pi}}, \\
Q_2^{\{1\}}(x, y) &= -\frac{1}{\sqrt{2\pi}}.
\end{aligned}$$

We also verified by computer algebra that the nonlinear connection Lemma is valid for arbitrary σ with $\sigma[[-1]] < 5$.

-
- [1] D. Gómez-Ullate, Y. Grandati, and R. Milson. Rational extensions of the quantum harmonic oscillator and exceptional hermite polynomials. *Journal of Physics A: Mathematical and Theoretical*, 47(1):015203, 2014.
 - [2] J.F. Carinena, A. M. Perelomov, and M.F. Ranada. Isochronous classical systems and quantum systems with equally spaced spectra. In *Journal of Physics: Conference Series*, volume 87, page 012007. IOP Publishing, 2007.
 - [3] S. Yu. Dubov, V.M. Eleonskii, and N.E. Kulagin. Equidistant spectra of anharmonic oscillators. *Chaos: An Interdisciplinary Journal of Nonlinear Science*, 4(1):47–53, 1994.
 - [4] V.G. Bagrov and B.F. Samsonov. Darboux transformation of the schrödinger equation. *Physics of Particles and Nuclei*, 28(4):374–397, 1997.
 - [5] A.A. Andrianov and M.V. Ioffe. Nonlinear supersymmetric quantum mechanics: concepts and realizations. *Journal of Physics A: Mathematical and Theoretical*, 45(50):503001, 2012.
 - [6] A. Das and W.-J. Huang. Propagators for shape-invariant potentials. *Phys. Rev. D*, 41:3241–3247, May 1990.
 - [7] A. M. Jayannavar and A. Khare. Propagators for shape-invariant singular potentials. *Phys. Rev. D*, 47:4796–4797, May 1993.
 - [8] A. M. Pupasov, B.F. Samsonov. Exact propagators for soliton potentials. *SIGMA. Symmetry, Integrability and Geometry: Methods and Applications*, 1:020, 2005.
 - [9] B.F. Samsonov, C.V. Sukumar, and A.M. Pupasov. SUSY transformation of the green function and a trace formula. *Journal of Physics A: Mathematical and General*, 38(34):7557, 2005.
 - [10] B.F. Samsonov and A.M. Pupasov. Exact propagators for complex SUSY partners of real potentials. *Physics Letters A*, 356(3):210–214, 2006.
 - [11] A.M. Pupasov, B.F. Samsonov, and U. Günther. Exact propagators for SUSY partners. *Journal of physics A: Mathematical and Theoretical*, 40(34):10557, 2007.
 - [12] R. P. Feynman. Space-time approach to non-relativistic quantum mechanics. *Reviews of Modern Physics*, 20(2):367, 1948.
 - [13] D. Gomez-Ullate, N. Kamran, and R. Milson. Exceptional orthogonal polynomials and the Darboux transformation. *Journal of Physics A: Mathematical and Theoretical*, 43(43):434016, 2010.
 - [14] A.A. Andrianov and A.V. Sokolov. Nonlinear supersymmetry in quantum mechanics: algebraic properties and differential representation. *Nuclear Physics B*, 660(1):25–50, 2003.

- [15] V.G. Bagrov and B.F. Samsonov. Darboux transformation, factorization, and supersymmetry in one-dimensional quantum mechanics. *Theoretical and Mathematical Physics*, 104(2):1051–1060, 1995.
- [16] S. Roman. The umbral calculus. *Advances in Mathematics*, 27(2):95 – 188, 1978.
- [17] J.F. Carinena, A.M. Perelomov, M.F. Ranada, and M. Santander. A quantum exactly solvable nonlinear oscillator related to the isotonic oscillator. *Journal of Physics A: Mathematical and Theoretical*, 41(8):085301, 2008.
- [18] C. Grosche and F. Steiner. Handbook of Feynman path integrals. *Springer tracts in modern physics*, 145:1, 1998.
- [19] S. Roman. The theory of the umbral calculus. I. *Journal of mathematical analysis and applications*, 87(1):58–115, 1982.
- [20] We assume that V_σ is defined for all $x \in \mathbb{R}$, which restricts possible choice of σ , in particular, $|\sigma| = 2M$. See for the details [1]